

Xpedite

ROOTING GUIDE

Copyright © 2013 X-TEL Communications, Inc. All Rights Reserved.

www.x-tel.com



Download needed software

1. Go to autoroot.chainfire.eu The is an array that lists a lot of different devices. Find you device and download the file.

) (-) 🌔	http://autoroot.cha	infire.eu/		0-2C	🙆 CF-Auto-Roo	ıt	×			
company	10170200	parent.	han	1000000	managood	010 11		10000100	110-101010	200210
samsung	GT-19505G	jgediteue	jgedite	MSM8960	msm8960	112 +1	76 +1	19881545	File - Forum	5147
samsung	GT-N5100	kona3giox	kona3g	smdk4x12	exynos4	238 +1	203 +1	12703820	File - Forum	67534
samsung	GT-N5110	konawiftox	konawifi	smdk4x12	exynos4	219 +1	187 +1	12608905	File - Forum	24265
samsung	GT-N5120	konaltero:	konalte	smdk4x12	exynos4	235 +1	163 +1	12796589	File - Forum	11913
samoung	GT-N7100	103gcc	103g	smdk4x12	exynos4	903 +1	495.+1	13958823	File - Forum	502670
samsung	GT-N7100T	t03gdo	t03g	smdk4x12	exynos4	310 +1	272 +1	13340891	File	1376
samsung	GT-N7102	t03gduoszc	t03gchnduos	smdk4x12	exynos4	290 +1	268 +1	13409293	File	7372
samsung	GT-N7105	tOttexx	t0ite	smdk4x12	exynos4	418 +1	345 +1	14035697	File - Forum	104117
samsung	GT-N7105T	t0ltedv	tüte	smdk4x12	exynos4	312 +1	301 +1	13418189	File	2941
samsung	GT-N8000	p4notertox	p4noterf	smdk4x12	exynos4	371 +1	333 +1	12101200	File - Forum	91999
samsung	GT-N8010	p4notewifixx	p4notewifww	smdk4x12	exynos4	364 +1	307 +1	12035397	File - Forum	24802
samsung	GT-N8013	p4notewifue	p4notewifi	smdk4x12	exynos4	298 +1	283 +1	12037569	File - Forum	16469
samsung	GT-N8020	p4noteltexx	p4notelte	smdk4x12	exynos4	300 +1	311 +1	12260553	File - Forum	6768
samsung	GT-P3100	espressorfox	espressorf	piranha	omap4	362 +1	340 +1	11704123	File - Forum	202346
samsung	GT-P3110	espressowificx	espressowifi	piranha	omap4	384 +1	322 +1	11701125	File - Forum	81161
samsung	GT-P3113	espressowifue	espressowifi	piranha	omap4	347 +1	304 +1	11711116	File - Forum	45901
				-					-	

MAKE SURE YOU DOWNLOAD THE CORRECT FILE

2. Unzip the file you just downloaded. Now you should have a .exe file and a .tar.md5 file.

CF-Auto-Root-ja3g-ja3goo-gti9500			
Organize 🔻 Burn New folder			
 ★ Favorites ■ Desktop → Downloads ★ Recent Places 	CF-Auto-R oot-ja3g-ja 3gx-gti950 0.tar.md5	Odin3	Gdin3-v1.8
Libraries Documents			



Get your device ready for rooting

1. Turn on USB debugging

Go Apps > Settings > Developer Options. If Developer options menu is not visible on your device, go Apps > Settings > About Device and scroll down to the **Build Number**. Now tap it five times and you should see a notification saying **Developer mode has been enabled**. Now turn on **USB debugging**.

2. Switch your device in download mode

- Power off

- Hold Volume down + Home + Power until you will see the following screen.

3. Press volume up

You should see the following screen.



Rooting

Odin3 v1.85	
CF-Auto-	Root-ja3g-ja3gxx-gti9500
D.COM	
Johon Auto Reboot F. Reset Time Planh Lock Dump APRAM Plane EFS Clear Phone Bootboader Update Versage 4D0/0033> Added11	Control Panel Start Reset PTT File [Download]

1. Connect your device to your PC via USB cable.

Xpedite

2. Run the .exe file (the one you previously downloaded).

3. **Push PDA button**, select the .tar.md5 file and push Start. Flashing your device will take a little while.

Gongratulations you have now sucessfully rooted your device!

Thank You for choosing Xpedite!

For more information about Xpedite and other X-TEL products please visit: WWW.X-tel.COM